

PLA-240

Small Room Loop Amplifier System

USER MANUAL



Overview

Thank you for purchasing the PLA 240 Small Room Loop Amplifier System.

The PLA 240 Loop System provides a practical solution for hearing aid users to listen more easily to their TV or audio equipment via the “T” or “Loop “ program of their hearing aid.

With no direct connection between the user and a TV or Audio equipment the user is able to move freely with the looped area and listen comfortably to a TV or audio equipment without the distractions of normal listening.

The Loop System is used in conjunction with a hearing aid with a “T” or “Loop” program found on many ‘behind the ear’ or ‘in the ear’ hearing aids. The loop system picks up the sound from a TV via a direct connection or microphone and feeds it to the amplifier. The sound is then passed to a loop of wire around the listening area, which in turn transmits the sound inductively (magnetic sound waves) to a hearing aid with the loop facility. The user may then adjust the loop volume or tone to suit their own hearing preference without affecting others.

The Loop System is supplied with loop wire.

The loop wire is placed around the inside perimeter of a room that you want to listen in. The sound can be heard anywhere inside the “looped” area and sometimes just outside the loop as well.

Quick Setup

1. Check contents of package.
2. Place amplifier near TV or Audio equipment.
3. Connect audio leads between TV or Audio system with Loop Amplifier.
4. Place loop cable around room and connect both ends of wire to loop cable connectors on the rear of the loop amplifier.
5. Plug the power supply unit lead into the amplifier. Connect the line cord to the power supply unit and place the barrel plug into the power jack on the rear of the amplifier.
6. Switch on TV / Audio equipment and Loop Amplifier.
7. Select the source button(s) on front of amplifier corresponding to your audio inputs.
8. Switch hearing aid to T or Loop program.
9. Adjust loop amplifier volume/tone to suit listening preference.

Safety Instructions

Williams AV cannot be held responsible for damage which is caused by not using this Loop System in compliance with these safety instructions.

IF IN ANY DOUBT SEEK EXPERT ADVICE

1. Read and follow these instructions taking note of any warnings. Keep these instructions for future reference.
2. Do not use the system or accessories near water.
3. Do not expose the system or accessories to rain or any other source of moisture.
4. Should the amplifier require cleaning only do so with a dry cloth.
5. Ensure that there is enough room around the Loop Amplifier for ventilation purposes.
6. Do not cover the ventilation holes of the amplifier.
7. Do not place the Loop Amplifier close to sources of heat, such as radiators.
8. Place all connecting and power leads such that they are not a hazard or where they may become damaged.
9. Do not open the case of the loop amplifier at any time; there are no user-servicable parts
10. Servicing must be referred to qualified service personnel.
11. Batteries should not be exposed to excessive heat such as sunshine or fire.

 **CAUTION:** Ensure the line cord is disconnected BEFORE any audio connections are made to the Loop Amplifier. To completely disconnect the system from the line cord, please remove the line cord plug from the wall socket.

 **CAUTION:** The top surface of the amplifier may become hot when operating this system continuously. Do not touch the top surface during use or block the ventilation holes.



Recycling Instructions


Help Williams AV protect the environment! Please take the time to dispose of your equipment properly.




Product Recycling: Please do NOT dispose of your Williams AV equipment in the household trash. Please take the equipment to an electronics recycling center; OR, return the product to the factory for proper disposal.

Connect Loop Wire to the Loop Output Terminals

Push the tabs in (toward the amplifier) to open the hole and allow the wire in. Ensure that only the bare wire goes into the hole and not the insulation. Release the tab to bind the wire in the hole.



Connect Audio Outputs from TV or other audio source to Loop Amplifier Inputs



Direct audio connections

This is the preferred method of connecting the amplifier to a TV and other audio products (as opposed to using a microphone). It will deliver the clearest sound without background noise affecting the clarity. The amplifier has both analog and digital audio inputs.

Digital Optical TOS link and Coaxial outputs are found on most TVs and Audio Equipment. These connections will provide the clearest sound input to your system. You may need to alter the settings of the digital audio output on your TV to "PCM" so that the digital audio output signal matches the loop amplifier.

Analog audio connections use the red, white RCA Audio connectors on the loop amplifier. These analog audio connections are very common on all types of equipment.

Multiple pieces of equipment may be connected to the loop amplifier at any one time:

- One digital source using either TOSlink or Coaxial but NOT both at the same time
- One or two pieces of analog equipment using the analog audio inputs
- One or two microphones

The sources may be switched by using the input buttons on the front of the unit. One microphone (Microphone B) can override all other sources by depressing the priority switch on the back of the unit.

Note when using a television as a source, and using the TV's headphone jack output, this connection may disable the television speaker from working. On some TVs there is a setup option in the TV menu that allows the TV speaker to keep working while the headphone jack is being used.

Microphones

If a direct connection is not possible then a microphone can be used to pick up the sound from a TV or other loudspeaker. Microphones can also be used for someone to speak directly into the loop system so they can speak directly to the hearing aid user when they listen to TV. A microphone can be used at the same time as the line inputs to monitor other sounds such as a doorbell or telephone ringer.

A microphone can also be used in either a classroom or public speaking situations.

One or two microphones can be used at the same time using the microphone jacks.

A priority function also exists when using a microphone in jack "B" to override sounds from any other input to the loop amplifier.

Connect Power to the Amplifier

Plug the power supply plug into the jack on the rear of the amplifier. Plug the line cord into the jack on the power supply and plug the other end into the wall jack. Switch on the unit by pushing the power button on the front right side of the unit.

Operation

When connecting power for the first time to your amplifier the power button will illuminate blue and the amplifier will be On. This is normal operation and is intended for situations where


remote switching of AC power happens and the unit needs to power-up in the “On” state.

Pressing the power button on the amplifier will change the color to red and the amplifier will be in standby mode which (1) uses low power and (2) no signal will be passed to the loop.

Press the power button again and it will light up blue. The system is now ready for use.

1. Set the television or other audio equipment to normal listening level for the other listeners in the room.
2. Select the sound source required from either the front buttons.
3. Set the volume control to minimum.
4. Set the tone control to normal position (12 o'clock).
5. Switch your hearing aid to the T or loop function.
6. Adjust the volume to suit your listening with the front knob.

Pressing the power button will turn the amplifier off and the light will glow red. The next time the power is turned on the volume, tone and source selections from the previous session will be restored.



Volume Control

Use to adjust the volume of the signal received by the hearing aid. As the volume control is moved the blue light will travel around the control indicating the volume level in use.

Tone Control

Use to vary the tone of the signal. When turned in a clockwise direction the higher frequencies will be emphasized, and in the counterclockwise position the lower frequencies will be emphasized. As the tone control is moved the blue light will travel around the control indicating the tone level in use.

Source Selection Buttons

Pressing any one of the input buttons (Mic Input, Line Input A Line Input B, Digital Input C) will select the audio source connected to the corresponding jack on the rear of the amplifier. One or more of these can be selected at any one time. When the source is selected a blue light will show in the button. Press the button again and the blue light will go out, indicating that source is off.

Microphone

Selecting this source will allow sound from the microphones connected to the mic jacks on the rear of the amplifier to be heard through the system. When a microphone is plugged into the "Mic B" jack, and the priority button is pushed, any sound received by this microphone will override all other sources connected to the system. This can be useful for monitoring a doorbell, or if a partner wants to talk to the hearing aid wearer through the loop.

Analog Inputs (Line Input A, Line Input B)

Selecting these sources will allow sound from the corresponding jacks on the rear of the amplifier to be heard through the system. These inputs are useful to connect a TV or DVD player so that either may be easily selected from the front panel. Either or both channels can be selected (and heard) simultaneously.

Digital Inputs (Coaxial or Optical)

Allows selection of digital audio from the corresponding jacks on the rear of the amplifier to be heard - but not both jacks at the same time. When selected the light on the button will turn blue. If the light glows red then there is no audio being received from the digital equipment by the amplifier.

Headphone Jack

The headphone jack may be used with stereo headphones that have a 3.5 mm plug. This may be used by a non-hearing aid user to monitor or listen to received sound. This can also be used for troubleshooting - to verify if sound is being received by the currently selected input(s). Listening with headphones does not affect the performance of the loop system for hearing aid

user(s). The headphone jack may be used without a loop wire connected but the loop level indicator will not show.

Troubleshooting

Problem	Solution
No Sound	<ul style="list-style-type: none">-Re-Check all connections-Check diagrams-Amplifier not switched on or no power-Microphone or audio source not connected or selected-Check Digital Audio setting on TV is "PCM"-Hearing Aid not on the "T" or Loop Program-Volume is muted
Low Sound	<ul style="list-style-type: none">-Microphone too far from sound-Loop wire not connected correctly-Volume set too low - increase volume-TV or audio source volume set too low - increase volume on source
Distorted Sound	<ul style="list-style-type: none">-Volume control set too high. Loop level indicator showing solid (not flickering) - decrease volume-TV/Audio source volume set to high - decrease-Microphone too close to loudspeaker - move away-Microphone plug damaged-Too many inputs in use at once - select less or reduce volume on all
Background noise (hum or buzz)	<ul style="list-style-type: none">-If noise remains when the loop system is turned off but hearing aid is still on loop program, this interference is caused by other equipment such as florescent lights or dimmer switches. With the loop amplifier turned off and the hearing aid still on the loop program, turn suspected items off, one-by-one, until the interference source can be identified-If noise stops when the loop amplifier is turned off there may be a fault in the system or microphone lead or noise is being picked up by the microphone

Specifications

Power Supply	<ul style="list-style-type: none">- Unit requirements: 18 V, 1.5 A- External Power Supply: 12-24 VDC, 2 A
Controls	<ul style="list-style-type: none">- Rotary Volume Control- Rotary Tone Control- On/Off Power Button- Source Selection Button- Priority Button
Input connections	<ul style="list-style-type: none">- Digital Audio TOSlink/Coaxial- 2x Microphone inputs, 3.5 mm jack plug, DC powered 5V for electret microphones- 2x Aux In Left/Right line inputs. RCA jacks for direct connection to a TV or sound output or other audio source
Output connections	<ul style="list-style-type: none">- Push grip connectors for loop wire (labelled "loop cable"). Required loop resistance 0.5 - 1.5 ohms.- 3.5 mm stereo jack for headphones (8-60 Ohms)
Loop output	<ul style="list-style-type: none">- 3.0 A output current @ 100 Hz - 5 kHz. Meets ADA 60118-4; 2006 for a loop not exceeding 20 ft (6.5 m) in width. Suitable for areas up to 750 sq ft (70 m²).
Loop wire	Single turn loop wire. System supplied with 130 ft (40 m) of 24 ga/0.75 mm ² single core PVC insulated wire. Min wire length 36 ft (11m) = 0.5 Ohms.
Indicators	<ul style="list-style-type: none">- Blue/Red LEDs

Warranty

Williams AV products are engineered, designed, and manufactured under carefully controlled conditions to provide you with many years of reliable service. Williams AV warrants the PLA 240 modulator against defects in materials and workmanship under normal use and conditions for the 2-years from the product from date of purchase.

This warranty is available to the original end purchaser of the product and can be transferred to subsequent purchasers of the product. Microphones, earphones, headphones, batteries, chargers, cables, carry cases, and most other accessory products carry a 90-day warranty.

Williams AV has no control over the conditions under which this product is used. Williams AV, therefore, disclaims all warranties not set forth above, both express and implied, with respect to the PLA 240, including but not limited to, any implied warranty of merchantability or fitness of use of such equipment including, without limitation, any warranty that the use of such equipment for any purpose will comply with applicable laws and regulations. Williams AV shall not be liable to any person or entity for any medical expenses or any direct, incidental or consequential damages caused by any use, defect, failure or malfunctioning of the product, whether a claim for such damages is based upon warranty, contract, tort or otherwise, the sole remedy for any defect, failure or malfunction of the products is replacement of the product. No person has any authority to bind Williams AV to any representation or warranty with respect to the PLA 240 System. Unauthorized repairs or modifications will void the warranty. This warranty is void if damage occurred because of misuse, or if the product has been repaired or modified by anyone other than a factory authorized service technician. Warranty does not cover normal wear and tear on the product or any other physical damage unless the damage was the result of a manufacturing defect. Williams AV is not liable for consequential damages due to any failure of equipment to perform as intended. Williams AV shall bear no responsibility or obligation with respect to the manner of use of any equipment sold by it.

This warranty does not cover reimbursement for your costs of removing and transporting the product for warranty service evaluation or installation of any replacement product provided under this warranty.

The exclusions and limitations set out above are not intended to, and should not be construed so as to contravene mandatory provisions of applicable law. If any part or term of this Disclaimer of Warranty is held to be illegal, unenforceable, or in conflict with applicable law by a court of competent jurisdiction, the validity of the remaining portions of this Disclaimer of Warranty shall not be affected, and all rights and obligations shall be construed and enforced as if this warranty did not contain the particular part or term held to be invalid. The terms of the warranty are governed by the laws of the State of Minnesota.

Prices and the specifications of the products are subject to change without notice. For Complete Warranty Statement go to: <https://williamsav.com/support/warranty-product-registration/>

NOTICE: Williams AV products are NOT designed for use in extreme temperature, humidity or chemical environments. The introduction of chemicals such as chlorine, salt water or human sweat into the product will cause damage to the circuitry. Damage due to these causes is NOT covered under the Product Warranty.

If you experience difficulty with your system, call Toll-Free for Customer Assistance

1-800-843-3544 (U.S.A.) or +1 952 943 2252 (Outside the U.S.A.)

If it is necessary to return the system for service, your Customer Service Representative will give you a Return Authorization Number (RA) and shipping instructions.

WILLIAMS AV

info@williamsav.com / www.williamsav.com

800-843-3544 / INTL: +1-952-943-2252

© 2020, Williams AV, LLC MAN 211C