## WILLIAMSAV

### SPECIFICATION DATA

# CHG 428 Charging Bay



Charging bay for WaveCAST Receivers and Digi-Wave DLT 400 and DLR 400 RCH.

### CHG 408

8.3"L x 5.5"W x 1.2"H (210 mm x 140 mm x 29.5 mm)
0.90 lbs (0.4 kg)
Black and dark transparent plastic dividers
18-20V DC
5V DC/1A for black USB ports, 5V DC/2.4A for red USB ports
8 Units
One LED for indicating power to charger; no individual indicators.
CHG 408 WF: WF R1 CHG 408 DW: DLT 400, DLR 400 RCH (Appropriate USB cables can be used with any CHG 408. See Note.)
1 year (90 day warranty on cables and power supply)
WEEE, RoHS, CE, FCC, IC, Japan
Accepts USB type A plugs, with a USB-C or with a micro-B plug that can connect to the device to be charged.

### WILLIAMSAV

### SPECIFICATION DATA

#### **Architecture and Engineering Specifications**

- The charger shall be a 8-bay, drop-in charger for use with the WF R1, DLT 400, and DLR 400 RCH.
- The charger be enclosed in black with dark transparent plastic dividers.
- The charger shall be 8.3"L x 5.5"W x 1.2"H (210 mm x 140 mm x 29.5 mm) and weigh 0.9 lbs (0.4 kg), excluding power supply.
- The charger shall be powered by an external power supply (18-20V DC input; 5V DC/1A for black USB ports, 5V DC/2.4A for red USB ports output) via a DC barrel connector.
- The charger shall have CE approval and be RoHS, WEEE, Japan, IC and FCC compliant.
- This charger shall be the Williams Sound model CHG 408.

#### **Domestic Sales**

Williams AV 10300 Valley View Rd Eden Prairie, MN 55344 Ph: 800-328-6190 / 952-943-2252 FAX: 952-943-2174 Email: info@williamsav.com Web: www.williamsav.com

### International Sales International Sales Department Williams AV 10300 Valley View Rd Eden Prairie, MN 55344 USA Phone: +1 952 943 2252 Fax: +1 952 943 2174 Email: info@williamsav.com Web: www.williamsav.com

